



Visit product page



I MIX 8

L005641

Compact, portable mixing console, 4 mono + 2 stereo input, 1bus, USB/SD Player and Bluetooth, A/D&D/A converter sample freq .24-Bit,16 programs

TECHNICAL DETAILS

Technical Specifications

Inputs: 8.
Mic Input channels: 4.
Stereo Input channels: 2.
Gain: MIN - MAX.
Mic: +6dB - +50dB.
Line: +10dB - -34dB.
EIN: -100dB.

Frequency response

Mic Channel: 10Hz - 20kHz +1/-3.
THD Mic Channel: $\leq 0.03\%$.
Signal to noise ratio: 80dB.
Output Levels: MAX +27(BAL)

Channel EQ

Hi: MAX +22(UNBAL).
Mid: 12kHz.
Lo: 2.5kHz.
Lo Cut: 45Hz.

MP3/USB/SD Audio, Playback.

USB/SD Audio recording

DSP Effects

Power requirements: 100 / 240 Volt AC

Dimensions (W x H x D): 283 x 70 x 359 mm.

PHOTOS



PRODUCT VIDEO



ACCESSORIES



I MIX 8 Rack

Rack brackets for i mix 8 mixing console.

