



Visit product page

## IPA-240

L005751



Public Address mixer amplifier 240w , 100V / 70V constant voltage output, 8 ohm constant resistance output, mp3, bluetooth, FM tuner ,USB interface,LCD screen, 3 line input, 2 mic input, 1 line output.Treble and Bass,IR control function

### TECHNICAL DETAILS

#### Technical Specifications

Rated Power: 240 Watt.

Mic input: -60dB, 6000, unbalanced, 6.3mm TS port.

Aux input: -20dB, B310kΩ, unbalanced, Stereo RCA port.

Aux output: 0dB, 6000, unbalanced, Stereo RCA port.

Speaker output: High Impedance: 100V, 70V; Low Impedance: 8Ω.

Protection: AC fuse, overheating, overvoltage, overcurrent, short, DC, and muting during power on protections.

Effects: 5 EQ sound effector for MP3 player and FM tuner audio output.

EQ for Master Output: Treble:± 12dB at 10kHz; Bass: ± 12dB at 100Hz.

Frequency response: 20-20kHz (±3dB).

S/N: Microphone input >66dB; AUX input>75dB.

T.H.D.: <0.5% at 1 kHz, at 1/3 rated power.

Power Source: 220-240VAC, 50/60Hz.

Power consumption: 250 Watt at rated power.

Weight: 10 Kg.

Temperature / Humidity operation condition: -10°C - +40°C, <95%.

Dimensions: 482(W) x 70(H) x 310(O) mm.

Shipping weight: 10 Kg.

Shipping dimensions: 0.0299CBM, 58(W) x 43(H) x 12(O) cm.

# PHOTOS



# PRODUCT VIDEO

